# Event-triggered state estimation for nonlinear systems aided by machine learning

D.C. Huong, T.N. Nguyen, H.T. Le

Abstract—This paper considers the event-triggered state estimation problem with the aid of machine learning for nonlinear systems subject to external disturbances in the state and output vectors. First, we develop a recurrent neural network (RNN) learning algorithm to predict the nonlinear systems. Second, we design a discrete-time event-triggered mechanism and a state observer based on this mechanism for the RNN model. This discrete-time event-triggered state observer significantly reduces the utilization of communication resources. Third, we establish a sufficient condition to ensure that the state observer can robustly estimate the state vector of the recurrent neural network. Finally, we provide an illustrative example to verify the merit of the proposed method.

# *Index Terms*—Nonlinear systems, discrete-time event-triggered mechanism, disturbances, linear matrix inequality (LMI).

In many engineering fields, the information of state vectors of dynamical systems is usually required for control design or fault detection. However, due to technical or economic reasons, the true state vectors of the systems are not available. Therefore, dynamical state estimation becomes an important application in different areas ranging from control engineering, robotics, tracking and navigation (see, for example, [1], [2], [3], [4]).

There are many approaches in the literature dealing with the design of state observers for the purpose of state estimation (see, for example, [5]-[14]). It is noted that all the state observers in the references [5]-[14] are designed based on time-triggered schemes, i.e., observer designs require system data for each sampling instant, which may lead to the wastage of communication resources in practical applications. To overcome this drawback, some event-triggered state observers were proposed [15]-[26] in order to maintain the desired performance while reducing the utilization of communication resources. In particular, an event-triggered extended state observer was proposed in [15] for nonlinear systems with disturbances, where nonlinear functions are continuously differentiable, while a robust state observer on the basis of the continuous dynamic event-triggered mechanism was designed in [16] for a class of nonlinear systems where the nonlinear function satisfies the one-sided Lipschitz and quadratically inner-bounded conditions. Noting that the nonlinear functions in [15] and [16] have some restriction, therefore the eventtriggered state observers in these references cannot applied to general nonlinear systems. Moreover, since the dynamic event-triggered mechanism in [16] depends on continuous supervision of the event-driven condition, it may cause strict requirement for driven-condition.

On the other hand, in recent years, machine learning has attracted a lot of research attentions due to the increase in its applications in many fileds as fault-tolerant control, cybersecurity, real-time control, and optimization problems. With the rapid development of computational resources, machine learning techniques have been widely utilized to solve important problem such as classification and regression. RNNs are belong to machine learning techniques which have received considerable attention in recent years due to their advantages in learning ability, parallel computation, industrial automation, and function approximation [27], [28], [29], [30]. Recently, in [31], the authors considered the design of model predictive control systems for nonlinear processes that utilize an ensemble of models to predict nonlinear dynamics. They first trained a RNN model by using extensive open-loop simulation data to capture process dynamics in a certain operating region such that the modeling error between the RNN model and the actual nonlinear process model was sufficiently small. Then, they utilized the RNN model as the prediction model in order to achieve closed-loop state boundedness and convergence to the origin. However, [31] did not consider the issue of external disturbances in the RNN as well as the design of discretetime event-triggered state observers for the RNN prediction model.

Motivated by the works [15], [16] and [31], in this paper, we focus on the design of discrete-time event-triggered state observers for the nonlinear systems subject to external disturbances with the aid of machine learning. The contributions of this paper are: (1) The nonlinear system is predicted by a RNN model subject to external disturbances; (2) a discretetime event-triggered mechanism is designed and utilized for designing event-triggered state observers of the RNN model; (3) the event-triggered the observer is new and can reduce the utilization of communication resources while maintaining the desired robust estimation performance; and (4) a sufficient condition for the existence of the event-triggered state observer is established and unknown observer matrices are obtained by solving a convex optimization problem.

Notation: For a matrix A,  $A^T$  denotes its transpose.  $\mathbb{R}^n$  is the n- dimensional linear vector space over the reals with the Euclidean norm. ||x|| denotes Euclidean norm of vector  $x \in \mathbb{R}^n$ . If  $x^T P x > 0, \forall x \neq 0$ , then matrix P is called positive definite and denoted by P > 0. sym $\{M\}$  denotes the notation  $M + M^T$ . \* denotes the entries of a matrix implied by symmetry.  $||g||_{\mathcal{L}^n_2} = \sqrt{\int_0^\infty g^T(t)g(t)dt}$  is the  $\mathcal{L}^n_2$  norm of

D.C. Huong, T.N. Nguyen, H.T. Le are with the Department of Mathematics and Statistics, Quy Nhon University, Binh Dinh, Vietnam (e-mail: dinhconghuong@qnu.edu.vn, tranngocnguyen@qnu.edu.vn, lethanhhieu@qnu.edu.vn).

the vector function  $g: [0,\infty) \to \mathbb{R}^n$  and  $\mathcal{L}_2^n = \{g: [0,\infty) \to \mathbb{R}^n: ||g||_{\mathcal{L}_2^n} < \infty\}.$ 

#### I. PRELIMINARIES AND PROBLEM STATEMENT

Let us consider the following nonlinear systems subject to disturbances

$$\dot{x}(t) = F(x, u, \omega) = f(x(t)) + g(x(t))u(t) + h(x(t))\omega(t), \ t \ge 0,$$
(1)

$$x(0) = x_0, \tag{2}$$

$$y(t) = Cx(t) + Ed(t), \tag{3}$$

where  $x(t) \in \mathbb{R}^n$  is the state vector,  $u(t) \in \mathbb{R}^m$  is the input vector,  $y(t) \in \mathbb{R}^p$  is the output vector,  $\omega(t) \in \mathbb{R}^{n_\omega}$  is the disturbance in the state vector,  $d(t) \in \mathbb{R}^{n_d}$  is the disturbance in the output vector.  $F(x, u, \omega)$  is a nonlinear function with respect to x, u and  $\omega$ .  $f(\cdot)$ ,  $g(\cdot)$ ,  $h(\cdot)$  are sufficiently smooth vector and matrix functions of dimensions  $n \times 1$ ,  $n \times m$  and  $n \times n_\omega$ , respectively.  $C \in \mathbb{R}^{p \times n}$ ,  $E \in \mathbb{R}^{p \times n_d}$  are constant matrices.

We need the following assumptions:

 $\begin{array}{l} (H_1) ||F(x,u,\omega)|| \leq M; \\ (H_2) ||F(z,u,\omega) - F(\bar{z},u,\omega)|| \leq L_z ||z - \bar{z}||, \ \forall z, \bar{z} \in D, \\ \forall u \in U \ \text{and} \ \forall \omega \in W, \ \text{where} \ D \ \text{is an open neighborhood} \\ \text{around the origin,} \ U = \{u \in \mathbb{R}^m : u_i \in [u_i^{\min}, u_i^{\max}], \ i = 1, 2, \dots, m\}, \ W = \{\omega \in \mathbb{R}^{n_\omega} : ||\omega|| \leq \bar{\omega}\} \ \text{and} \ M, \ L_z, \ \bar{\omega} \ \text{are} \\ \text{positive scalars.} \end{array}$ 

#### II. MAIN RESULTS

### A. Recurrent neural network (RNN)

Let us now consider the following RNN model which is utilized to approximate the nonlinear system (1):

$$\begin{aligned}
\tilde{x}(t) &= F_{rnn}(\tilde{x}, u, \omega) \\
&= A\tilde{x}(t) + \Theta^T \overline{y}(t), \ t \ge 0,
\end{aligned}$$
(4)

$$\tilde{x}(0) = x_0, \tag{5}$$

$$\tilde{y}(t) = C\tilde{x}(t) + Ed(t), \tag{6}$$

where  $\tilde{x}(t) \in \mathbb{R}^n$  is the RNN state vector,  $u(t) \in \mathbb{R}^m$  is the input vector,  $\overline{y}(t) = \begin{bmatrix} \overline{y}^1(t) & \overline{y}^2(t) & \overline{y}^3(t) \end{bmatrix}^T \in \mathbb{R}^{n+m+n_\omega}$ ,  $\overline{y}^1(t) = \begin{bmatrix} \overline{y}_1 & \dots & \overline{y}_n \end{bmatrix}^T = \begin{bmatrix} \sigma(\tilde{x}_1) & \dots & \sigma(\tilde{x}_n) \end{bmatrix}^T$ ,  $\overline{y}^2(t) = \begin{bmatrix} \overline{y}_{n+1} & \dots & \overline{y}_{n+m} \end{bmatrix}^T = \begin{bmatrix} u_1 & \dots & u_m \end{bmatrix}^T$ ,  $\overline{y}^3(t) = \begin{bmatrix} \overline{y}_{n+m+1} & \dots & \overline{y}_{n+m+n_\omega} \end{bmatrix}^T = \begin{bmatrix} \omega_1 & \dots & \omega_{n_\omega} \end{bmatrix}^T$ , where  $\sigma(\cdot)$  is the nonlinear activation function.  $A = \text{diag}\{-a_1, -a_2, \dots, -a_n\}$  and  $\Theta = \begin{bmatrix} \theta_1 & \dots & \theta_n \end{bmatrix} \in \mathbb{R}^{(n+m+n_\omega)\times n}$ ,  $\theta_i = b_i \begin{bmatrix} w_{i1} & \dots & w_{i(n+m+n_\omega)} \end{bmatrix}^T$ ,  $a_i > 0$ ,  $b_i$  are constants,  $w_{ij}$  is the weight connecting the *jth* input to the *ith* neuron,  $i = 1, \dots, n, j = 1, \dots, n + m + n_\omega$  are matrices to be optimized during training.

In this paper we assume that activation function  $\sigma(.)$  and external disturbance d(t) in the output vector satisfy the following assumptions:

 $(H_3)$  There are positive scalars  $\sigma_i > 0$  for i = 1, 2, ..., n such that

$$|\sigma_i(s_1) - \sigma_i(s_2)| \le \sigma_i |s_1 - s_2|, \forall s_1, s_2 \in \mathbb{R}.$$
 (7)

 $(H_4)$  The external disturbance d(t) is norm bounded, i.e. there exist a positive constant  $\bar{d}$  such that

$$||d(t)|| \le \bar{d}, \ \forall t \ge 0.$$
(8)

We now develop the RNN learning algorithm in [30], [31] to obtain an optimal weight matrix  $\theta_i^*$  such that state vector  $\tilde{x}(t)$  of the RNN can estimate state vector x(t) of nonlinear system (1). For this, we first express the dynamic behavior of each state of the system (1) by the following equation:

$$\dot{x}_i(t) = -a_i x_i + \theta_i^* \overline{y}(t) + \nu_i(t), \qquad (9)$$

where

$$\nu_i(t) = F_i(x, u, \omega) - (F_{rnn})_i(\tilde{x}, u, \omega), \qquad (10)$$

and optimal weight vector  $\theta_i^*$  is defined as below:

$$\theta_i^* = \arg \min_{|\theta_i| \le \theta_m} \left\{ \sum_{k=1}^N |F_i(x_k, u_k, \omega_k) + a_i x_k - \theta_i^T \overline{y}_k| \right\},$$
(11)

where  $\theta_m > 0$  and N is the number of data samples utilized for training.

It is assumed that RNN model (4) and nonlinear system (1) satisfy the following sufficiently small modeling error

$$||\nu(t)|| = ||F(x, u, \omega) - F_{rnn}(\tilde{x}, u, \omega)|| \le \bar{\nu}, \bar{\nu} > 0.$$
(12)

We now denote the state error as  $e(t) = \tilde{x}(t) - x(t) \in \mathbb{R}^n$ . Then, it follows from (4) and (9) that

$$\dot{e}_i(t) = -a_i e_i(t) + (\theta_i(t) - \theta_i^*)^T \overline{y}_i(t) - \nu_i(t).$$
(13)

The weight  $\theta_i(t)$  is updated during the training process as below:

$$\dot{\theta}_i(t) = -\eta_i \overline{y}(t) e_i(t), \ i = 1, 2, \dots, n, \tag{14}$$

where the learning rate  $\eta_i$  is a positive define  $(n+m+n_{\omega}) \times (n+m+n_{\omega})$  matrix.

The following lemma provides an upper bound for the error e(t):

*Lemma 3.* Let assumption  $(H_2)$  and condition (12) be satisfied. The following inequality holds:

$$||e(t)|| \le \frac{\bar{\nu}}{L_x} (e^{L_x t} - 1), \ t > 0.$$
(15)

*Remark 1:* In [31], the authors considered a RNN learning algorithm without external disturbances ( $\omega(t) \equiv 0$ ) for nonlinear systems with external disturbances of the form (1). Therefore, the error e(t) between state vector of the RNN and state vector of the nonlinear system satisfying the following inequality:

$$||e(t)|| \le \frac{L_{\omega}\bar{\omega} + \bar{\nu}}{L_x} (e^{L_x t} - 1), \ t > 0, \ \omega(t) \in W.$$
(16)

Unlike the method in [31], in this paper, we consider a RNN learning algorithm with external disturbances ( $\omega(t) \neq 0$ ) and thus, term  $L_{\omega}\bar{\omega}$  in the upper bound of the error e(t) in (16) is removed. The effect of the external disturbances will be minimized when we solve the robust state estimation for the RNN subject to external disturbances in the next section.

## B. Event-triggered state observers

Let us first express system (4)-(6) into the following form

$$\dot{\tilde{x}}(t) = A\tilde{x}(t) + \Theta_{\tilde{x}}\sigma(\tilde{x}(t)) + \Theta_{u}u(t) + \Theta_{\omega}\omega(t) \ t \ge 0,$$

$$\tilde{x}(0) = x_0, \qquad (17)$$

 $\tilde{y}(t) = C\tilde{x}(t) + Ed(t),$ 

where  $\begin{bmatrix} \Theta_{\tilde{x}} & \Theta_u & \Theta_\omega \end{bmatrix} = \Theta^T$ .

Next, we propose the following event-triggered state observer for system (17)-(18):

$$\dot{\hat{x}}(t) = A\hat{x}(t) + \Theta_{\tilde{x}}\sigma(\hat{x}(t)) + \Theta_{u}u(t) + L(\tilde{y}(t_{k}) - C\hat{x}(t_{k} + k(t)h), t \in [t_{k}, t_{k+1}),$$
(19)

where  $\hat{x}(t) \in \mathbb{R}^n$  is the estimate of  $\tilde{x}(t)$ , L is the gain matrix to be designed,  $k(t) = \lfloor \frac{t-t_k}{h} \rfloor = \max\left\{s \in \mathbb{N} \mid s \leq \frac{t-t_k}{h}\right\}$ ,  $\{t_kh\}_{k \in \mathbb{N}}$  ( $k \in \mathbb{N}$ ,  $t_0h = 0 < t_1h < \cdots < t_kh < \ldots$ ) is the measurement transmission instant sequence and consider the following event-triggered mechanism (ETM):

$$t_{k+1}h = \min_{\ell > t_k, \ \ell \in \mathbb{N}^+} \Big\{ \ell h \mid \mathcal{H}(\tilde{y}(\ell h), \tilde{y}(t_k), \delta(t_k)) > 0 \Big\}, \ k \in \mathbb{N},$$

$$(20)$$

where  $\delta(t_k) = \delta_1 + \delta_2 e^{-\delta_3 t}$  and  $\mathcal{H}(\tilde{y}(\ell h), \tilde{y}(t_k), \delta(t_k)) = \delta_4 ||\tilde{y}(\ell h) - \tilde{y}(t_k)||^2 - \delta_5 ||\tilde{y}(t_k)||^2 - \delta(t_k), \, \delta_i, \, i = 1, 2, 3, 4, 5$  are positive scalars.

The state observer (19) has a constraint that the current sampled measurement  $\tilde{y}(\ell h)$  is only transmitted when the event-triggered condition (20) is satisfied.

From the above definition of k(t), we have  $k(t) = \max_{\ell} \left\{ \ell \in \mathbb{N} \mid t_k \leq \ell h + t_k \leq t \right\}$ . This implies that

$$t - h < t_k + k(t)h \le t.$$
(21)

Let us define

$$e_{\tilde{y}}(t) = \tilde{y}(t_k) - \tilde{y}(t_k + k(t)h), \qquad (22)$$

$$\tau(t) = t - (t_k + k(t)h).$$
 (23)

Then we obtain  $0 \le \tau(t) < h$ .

By denoting  $\overline{x}(t) = \tilde{x}(t) - \hat{x}(t)$  and  $\sigma_{\tilde{x}z}^{\Delta}(t) = \sigma(\tilde{x}(t)) - \sigma(\hat{x}(t))$ , from (19), (22) and (23), we obtain

$$\dot{\overline{x}}(t) = A\overline{x}(t) + \Theta_{\tilde{x}}\sigma_{\tilde{x}z}^{\Delta}(t) + \Theta_{\omega}\omega(t) 
-LC\overline{x}(t-\tau(t)) - Le_{\tilde{y}}(t) 
-LEd_{\tau}(t), t \in [t_k, t_{k+1}),$$
(24)

$$\overline{x}(\theta) = \phi(0) - \psi(0), \ \theta \in [-h, 0],$$
 (25)

where  $d_{\tau}(t) = d(t - \tau(t))$ .

*Remark 2:* The discrete-time event-triggered state observer (19) is different from the one in [15], [16], [17], [18], since the term  $C\hat{x}(t)$  is replaced by  $C\hat{x}(t_k + k(t)h) = C\hat{x}(t - \tau(t))$ , which is more reality because the measurement received by the observers after a network delay  $\tau(t)$ .

In the following, we will design the gain matrix L such that, under zero initial condition, estimation error  $\overline{x}(t)$  with a time-varying delay  $\tau(t)$  satisfies the following inequality

$$||\overline{x}||_{\mathcal{L}_{2}^{n}} \leq \lambda_{\omega}||\omega||_{\mathcal{L}_{2}^{n\omega}} + \lambda_{d}||d||_{\mathcal{L}_{2}^{nd}},$$
(26)

where  $\lambda_{\omega} > 0$  and  $\lambda_d > 0$  will be optimized.

The following theorem allows us to obtain the gain matrix L and the minimized levels  $\lambda_{\omega}$  and  $\lambda_d$ .

Theorem 1. Let assumptions  $(H_3)$  and  $(H_4)$  be satisfied. For given positive numbers  $\beta$  and  $0 < \xi < 1$ , the event-triggered state observer design problem (26) with minimized levels  $\lambda_{\omega} > 0$  and  $\lambda_d > 0$  is solvable if there exist matrices P > 0, Q > 0, R > 0, Z, X, non-singular S and positive scalars  $\bar{\lambda}_{\omega}$ ,  $\bar{\lambda}_d$  and  $\epsilon$  such that the following convex optimization problem is feasible:

$$\min(\xi \bar{\lambda}_{\omega} + (1 - \xi) \bar{\lambda}_d)$$
subject to
$$(27)$$

$$\hat{\Xi}(\nu) = \begin{bmatrix} \Xi(\nu) & \nabla \\ * & -\epsilon I_n, \end{bmatrix} < 0, \ \forall \nu \in \{0, 1\}, \ (28)$$
$$\Delta = \begin{bmatrix} \operatorname{diag}(R, R) & Z \\ * & \operatorname{diag}(R, R) \end{bmatrix} > 0, \ (29)$$

where

(18)

$$\begin{split} \Xi(\nu) &= & \operatorname{sym}\{\Psi_{\nu}^{\tau}P\Gamma\} + e_{1}^{T}Qe_{1} - e_{3}^{T}Qe_{3} \\ &+h^{2}e_{4}^{T}R_{2}e_{4} - \Lambda^{T}\Delta\Lambda + e_{1}^{T}e_{1} - \lambda_{\omega}e_{8}^{T}e_{8} \\ &-\lambda_{d}e_{9}^{T}e_{9} - \operatorname{sym}\left\{\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}e_{4}\right\}, \\ &+\operatorname{sym}\left\{\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}Ae_{1} \\ &-\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{X}Ce_{2} \\ &-\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}\Theta_{\omega}e_{8} \\ &-\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}\Theta_{\omega}e_{8} \\ &-\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}\Theta_{\omega}e_{8} \\ &-\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{X}Ee_{9}\right\}, \\ &+\epsilon\sigma_{\max}^{2}e_{1}^{2}e_{1},\sigma_{\max}=\max\{\sigma_{1},\ldots,\sigma_{n}\}, \\ \overline{S}=\left[\begin{array}{cc} \beta S \\ S\end{array}\right], \ \overline{X}=\left[\begin{array}{cc} \beta X \\ X\end{array}\right], \\ &\Psi_{\nu}=\left[\begin{array}{cc} e_{1}^{T} & \nu he_{5}^{T} + (1-\nu)he_{6}^{T}\end{array}\right]^{T}, \\ &\Gamma=\left[\begin{array}{cc} e_{1}^{T} & (e_{1}^{T} - e_{3}^{T})\end{array}\right]^{T}, \ \Lambda=\left[\begin{array}{cc} \Lambda_{1} & \Lambda_{2}\end{array}\right]^{T}, \\ &\Lambda_{1}=\left[\begin{array}{cc} (e_{1} - e_{2})^{T} & \sqrt{3}(e_{1} + e_{2} - 2e_{5})^{T}\end{array}\right], \\ &\Lambda_{2}=\left[\begin{array}{cc} (e_{2} - e_{3})^{T} & \sqrt{3}(e_{2} + e_{3} - 2e_{6})^{T}\end{array}\right], \\ &\Lambda_{2}=\left[\begin{array}{cc} e_{1}^{T} & e_{4}^{T}\end{array}\right]\overline{S}\Theta_{\bar{x}}\left[\begin{array}{cc} I_{n} & 0_{n\times n}\end{array}\right], \\ &e_{i}=\left[\begin{array}{cc} e_{1}^{1} & e_{i}^{2}\end{array}\right]\in \mathbb{R}^{n\times(6n+p+n_{\omega}+n_{d})}, \\ &i=1,\ldots,6, \ e_{i}^{1}=\left[\begin{array}{cc} 0_{n\times(i-1)n} & I_{n}\end{array}\right], \\ &e_{7}=\left[\begin{array}{cc} 0_{p\times6n} & I_{p} & 0_{p\times(n_{\omega}+n_{d})}\end{array}\right] \\ &\in \mathbb{R}^{p_{\omega}\times(6n+p+n_{\omega}+n_{d})}, \\ &e_{8}=\left[\begin{array}{cc} 0_{n_{\omega}\times6n} & 0_{n_{\omega}\times p} & I_{n_{\omega}} & 0_{n_{\omega}\times(n_{\omega}+n_{d})}\end{array}\right] \\ &\in \mathbb{R}^{n_{\omega}\times(6n+p+n_{\omega}+n_{d})}. \end{array}$$

The observer gain matrix L is obtained as

$$L = S^{-1}X. ag{30}$$

**Proof.** Let us first denote  $\nu = \nu(t) = \frac{\tau(t)}{h}$ ,  $\tilde{e}(t) = \left[ \overline{x}^T(t) \quad \int_{t-h}^t \overline{x}^T(s) ds \right]^T$  and consider the following Lyapunov functional candidate:

$$V(t) = \tilde{e}^{T}(t)P\tilde{e}(t) + \int_{t-h}^{t} \overline{x}^{T}(s)Q\overline{x}(s)ds + h \int_{-h}^{0} \int_{t+\eta}^{t} \dot{\overline{x}}^{T}(s)R\dot{\overline{x}}(s)ds.$$
(31)

Taking derivative of V(t) in t, we obtain

$$\dot{V}(t) = 2\tilde{e}^{T}(t)P\dot{e}(t) + \bar{x}^{T}(t)Q\bar{x}(t) -\bar{x}^{T}(t-h)Q\bar{x}(t-h) + h^{2}\dot{x}^{T}(t)R\dot{x}(t) -h\int_{t-h}^{t}\dot{x}^{T}(s)R\dot{x}(s)ds$$
(32)  
$$= 2\zeta^{T}(t)\Psi_{\nu}^{T}P\Gamma\zeta(t) + \zeta^{T}(t)[e_{1}^{T}Qe_{1} - e_{3}^{T}Qe_{3}]\zeta(t) +h^{2}\zeta^{T}(t)(e_{4}^{T}Re_{4})\zeta(t) - h\int_{t-\tau(t)}^{t}\dot{x}^{T}(s)R\dot{x}(s)ds -h\int_{t-h}^{t-\tau(t)}\dot{x}^{T}(s)R\dot{x}(s)ds,$$
(33)

where

$$\begin{aligned} \zeta(t) &= \begin{bmatrix} \zeta_1(t) & \zeta_2(t) & \zeta_3(t) & \zeta_4(t) \end{bmatrix}^T, \\ \zeta_1(t) &= \begin{bmatrix} \overline{x}^T(t) & \overline{x}^T(t-\tau(t)) & \overline{x}^T(t-h) \end{bmatrix}, \\ \zeta_2(t) &= \begin{bmatrix} \dot{\overline{x}}^T(t) & \frac{1}{\tau(t)} \int_{t-\tau(t)}^t \overline{x}^T(s) ds \end{bmatrix}, \\ \zeta_3(t) &= \begin{bmatrix} \frac{1}{h-\tau(t)} \int_{t-h}^{t-\tau(t)} \overline{x}^T(s) ds \end{bmatrix}, \\ \zeta_4(t) &= \begin{bmatrix} e_{\tilde{y}}^T(t) & \omega^T(t) & d_{\tau}^T(t) \end{bmatrix}. \end{aligned}$$
(34)

From the Wirtinger-based integral inequality (see, [32]), we have

$$-h \int_{t-\tau(t)}^{t} \dot{\overline{x}}^{T}(s) R \dot{\overline{x}}(s) ds$$

$$\leq -h \Big\{ \frac{1}{\tau(t)} [\overline{x}(t) - \overline{x}(t-\tau(t))]^{T} R[\overline{x}(t) - \overline{x}(t-\tau(t))] + \frac{3}{\tau(t)} [\overline{x}(t) + \overline{x}(t-\tau(t)) - \frac{2}{\tau(t)} \int_{t-\tau(t)}^{t} \overline{x}^{T}(s) ds]^{T} R$$

$$\times \Big[ \overline{x}(t) + \overline{x}(t-\tau(t)) - \frac{2}{\tau(t)} \int_{t-\tau(t)}^{t} \overline{x}^{T}(s) ds \Big] \Big\}, \quad (35)$$

and

$$-h \int_{t-h}^{t-\tau(t)} \dot{\overline{x}}^{T}(s) R \dot{\overline{x}}(s) ds$$

$$\leq -h \Big\{ \frac{1}{h-\tau(t)} [\overline{x}(t-\tau(t)) - \overline{x}(t-h)]^{T} R$$

$$\times [\overline{x}(t-\tau(t)) - \overline{x}(t-h)] + \frac{3}{h-\tau(t)} \Big[ \overline{x}(t-\tau(t))$$

$$+ \overline{x}(t-h) - \frac{2}{h-\tau(t)} \int_{t-h}^{t-\tau(t)} \overline{x}^{T}(s) ds \Big]^{T} R$$

$$\times \Big[ \overline{x}(t-\tau(t)) + \overline{x}(t-h) - \frac{2}{h-\tau(t)} \int_{t-h}^{t-\tau(t)} \overline{x}^{T}(s) ds \Big]$$

Form (35) and (36), we obtain

$$-h \int_{t-\tau(t)}^{t} \dot{\bar{x}}^{T}(s) R \dot{\bar{x}}(s) ds$$
  

$$\leq -\frac{1}{\nu} \zeta^{T}(t) (e_{1} - e_{2})^{T} R(e_{1} - e_{2}) \zeta(t)$$
  

$$-\frac{3}{\nu} \zeta^{T}(t) (e_{1} + e_{2} - 2e_{5})^{T} R(e_{1} + e_{2} - 2e_{5}) \zeta(t),$$
(37)

and

$$-h \int_{t-h}^{t-\tau(t)} \dot{x}^{T}(s) R \dot{\overline{x}}(s) ds$$
  

$$\leq -\frac{1}{1-\nu} \zeta^{T}(t) (e_{2}-e_{3})^{T} R(e_{2}-e_{3}) \zeta(t)$$
  

$$-\frac{3}{1-\nu} \zeta^{T}(t) (e_{2}+e_{3}-2e_{6})^{T} R(e_{2}+e_{3}-2e_{6}) \zeta(t).$$
(38)

By using assumption  $(H_3)$  and Cauchy inequality [33], we obtain:

$$2e^{T}(t)\overline{S}\Theta_{\tilde{x}}\sigma_{\tilde{x}z}^{\Delta}(t) \leq \epsilon^{-1}e^{T}(t)\overline{S}\Theta_{\tilde{x}}\Theta_{\tilde{x}}^{T}\overline{S}^{T}e(t) + \epsilon(\sigma_{\tilde{x}z}^{\Delta}(t))^{T}\sigma_{\tilde{x}z}^{\Delta}(t) \leq \epsilon^{-1}e^{T}(t)\overline{S}\Theta_{\tilde{x}}\Theta_{\tilde{x}}^{T}\overline{S}^{T}e(t) + \epsilon\sigma_{\max}^{2}\overline{x}^{T}(t)\overline{x}(t).$$
(39)

Provided that  $\Delta > 0$ , from the reciprocally convex combination inequality [34], the following inequality is satisfied:

$$-h \int_{t-\tau(t)}^{t} \dot{\overline{x}}^{T}(s) R \dot{\overline{x}}(s) ds - h \int_{t-h}^{t-\tau(t)} \dot{\overline{x}}^{T}(s) R \dot{\overline{x}}(s) ds$$
  
$$\leq -\zeta^{T}(t) \Lambda^{T} \Delta \Lambda \zeta(t).$$
(40)

Denoting  $\overline{e}(t) = \begin{bmatrix} \overline{x}^T(t) & \dot{\overline{x}}^T(t) \end{bmatrix}^T$  and applying the free weighting matrix technique [35], from (24) we obtain

$$0 = 2\overline{e}^{T}(t)\overline{S} \Big[ -\dot{\overline{x}}(t) + A\overline{x}(t) + \Theta_{\omega}\omega(t) \\ -LC\overline{x}(t-\tau(t)) - Le_{\tilde{y}}(t) - LEd_{\tau}(t) \Big]$$
(41)  
$$= -2\overline{e}^{T}(t)\overline{S}\dot{\overline{x}}(t) + 2\overline{e}^{T}(t)\overline{S}A\overline{x}(t) \\ -2\overline{e}^{T}(t)\overline{X}C\overline{x}(t-\tau(t)) - 2\overline{e}^{T}(t)\overline{X}e_{\tilde{y}}(t) \\ + 2\overline{e}^{T}(t)\overline{S}\Theta_{\omega}\omega(t) - 2\overline{e}^{T}(t)\overline{X}Ed_{\tau}(t),$$
(42)

where S is a non-singular matrix with appropriate dimensions,  $\beta$  is a scalar and X = SL.

Let us denote  $\bar{\lambda}_{\omega} = \lambda_{\omega}^2$  and  $\bar{\lambda}_d = \lambda_d^2$ . From equations (35) to (42), we obtain

$$\dot{V}(t) + \overline{x}^{T}(t)\overline{x}(t) - \lambda_{\omega}^{2}\omega^{T}(t)\omega(t) -\lambda_{d}^{2}d_{\tau}^{T}(t)d_{\tau}(t) \leq \zeta^{T}(t)\hat{\Xi}(\nu)\zeta(t),$$
(43)

where  $\nu \in (0,1)$ .

Therefore, inequality

$$\dot{V}(t) + \overline{x}^{T}(t)\overline{x}(t) - \lambda_{\omega}^{2}\omega^{T}(t)\omega(t) - \lambda_{d}^{2}d_{\tau}^{T}(t)d_{\tau}(t) < 0$$
(44)

*ls*], is satisfied if  $\Delta > 0$  and  $\hat{\Xi}(\nu) < 0$ ,  $\forall \nu \in (0,1)$ . Since  $\hat{\Xi}(\nu)$ , is convex with respective to  $\nu$ ,  $\hat{\Xi}(\nu) < 0 \ \forall \nu \in \{0,1\}$  implies (36) $\hat{\Xi}(\nu) < 0 \ \forall \nu \in (0,1)$ .

By intergrating both sides of (44) from t = 0 to  $\infty$ , we obtain

$$V(\infty) - V(0) + ||\overline{x}||_{\mathcal{L}^{n}_{2}}^{2} - \lambda_{\omega}^{2}||\omega||_{\mathcal{L}^{n\omega}_{2}}^{2} - \lambda_{d}^{2}||d||_{\mathcal{L}^{nd}_{2}}^{2} \le 0.$$
(45)

Therefore, under zero initial condition, we obtain the following inequality

$$||\overline{x}||_{\mathcal{L}_{2}^{n}} \leq \lambda_{\omega}||\omega||_{\mathcal{L}_{2}^{n\omega}} + \lambda_{d}||d||_{\mathcal{L}_{2}^{nd}}.$$
(46)

Note that minimisation of  $\lambda_{\omega}$  and  $\lambda_d$  can be performed by minimisation of  $\bar{\lambda}_{\omega}$  and  $\bar{\lambda}_d$ , and the optimal value of  $\lambda_{\omega}$  and  $\lambda_d$  are obtained as  $\lambda_{\omega} = \sqrt{\bar{\lambda}_{\omega}}$  and  $\lambda_d = \sqrt{\bar{\lambda}_d}$ . Moreover, since S is invertible, from relation X = SL, the gain matrix L can be obtained as  $L = S^{-1}X$ . The proof is completed. The following algorithm allows us to design the event-

# Algorithm 1

Stage 1 (Estimating nonlinear systems by using RNN): Check assumptions  $(H_1)$  and  $(H_2)$ . Using the newly RNN to train the nonlinear systems, obtain a RNN of the form (22)-(23). Stage 2 (Designing an ETM): Given scalars h > 0,  $\delta_i$ ,

i = 1, 2, 3, 4, 5, obtain an ETM of the form (25). Stage 3 (Designing a dynamic state observer):

Step 1: Check conditions (7) and (8).

triggered state observer as defined in (19).

Step 2: Given a scalar  $0 < \xi < 1$  and a positive scalar  $\beta$ ,

solve the convex optimization problem (32)-(34) to obtain matrices P > 0, Q > 0, R > 0, S > 0, X, non-singular Sand positive scalars  $\bar{\lambda}_{\omega}$ ,  $\bar{\lambda}_d$ ,  $\delta$ , minimized levels  $\lambda_{\omega}$ ,  $\lambda_d$  and observer gain L.

Step 3: Obtain an observer of the form (24).

#### III. A NUMRICAL EXAMPLE

Consider nonlinear system of the form (1)-(3), where

$$\begin{split} F(x,u,\omega) &= \begin{bmatrix} F_1(x,u,\omega) \\ F_2(x,u,\omega) \\ F_3(x,u,\omega) \\ F_4(x,u,\omega) \end{bmatrix}, \\ F_1(x,u,\omega) &= -x_1(t)x_2(t) - 0.25\cos t, \\ F_2(x,u,\omega) &= -0.0081x_2(t) + 0.5\cos t, \\ F_3(x,u,\omega) &= 24.10^{-4}x_1(t) - 0.13x_3(t) \\ &+ 10^{-4}x_4(t) + 0.5\cos t, \\ F_4(x,u,\omega) &= -0.5x_4(t) + 0.5\sin t + 0.5\cos t \end{split}$$

For this example, we can check that assumptions  $(H_1)$ ,  $(H_2)$  satisfy on  $\mathcal{D} = \{x \in \mathbb{R}^4 | |x_i| \leq 35\}$  with  $M = 1.2252.10^3$ ,  $L_x = 8.3666$ , respectively.



Fig. 1.  $x_1(t)$  and  $\tilde{x}_1(t)$ 



By using (9), (11), (13) and (14), a RNN model of the form (17)-(18) which approximates the nonlinear system (1)-(3) is obtained, where

$$\begin{split} A &= & \operatorname{diag}\{-25.0022, -0.0081, -0.13, -0.5\}, \\ \Theta_{\tilde{x}} &= & \begin{bmatrix} 0.6516 & -0.3158 & -0.0236 & 0.0106 \\ 0 & -0.0001 & 0 & 0 \\ 0.044 & -0.0211 & -0.0013 & -0.0006 \\ 0.0001 & -0.0001 & 0 & 0 \end{bmatrix}, \\ \Theta_{u} &= & \begin{bmatrix} -0.007 \\ 0 \\ 0.0002 \\ 0.5 \end{bmatrix}, \Theta_{\omega} = \begin{bmatrix} -0.7642 \\ 1 \\ 1.0002 \\ 1 \end{bmatrix}. \end{split}$$

Figures 1-4 show the responses of  $x_1(t)$ ,  $x_2(t)$ ,  $x_3(t)$ ,  $x_4(t)$ and  $\tilde{x}_1(t)$ ,  $\tilde{x}_2(t)$ ,  $\tilde{x}_3(t)$ ,  $\tilde{x}_4(t)$ , respectively. It is clear from figures 1-4 that the RNN can estimate the four states of the nonlinear system subject to unknown disturbance  $\omega(t)$ , as expected.

Given scalars h = 0.02,  $\delta_1 = 0.1$ ,  $\delta_2 = 0.3$ ,  $\delta_3 = 0.2$ ,  $\delta_4 = 0.35$ ,  $\delta_5 = 0.4$ , we obtain an ETM of the form (20).

Let us consider the activation  $\sigma(.)$  as  $\sigma_i(x_i) = \tanh x_i(t)$ , i = 1, 2, 3, 4 and the external disturbance in the output vector as  $Ed(t) = 0.01 \sin t$ ,  $t \ge 0$ . It is hot hard to



Fig. 4.  $x_4(t)$  and  $\tilde{x}_4(t)$ 

see conditions (7) and (8) are satisfied. Given  $0 < \xi = 0.6 < 1$ and  $\beta = 10.5$ , by following Stage 3 of Algorithm 1, we obtain minimized levels  $\lambda_{\omega} = 0.4545$ ,  $\lambda_d = 1.3617 \times 10^{-4}$  and gain

matrix 
$$L = \begin{bmatrix} 10.3401 \\ -0.0240 \\ 1.1136 \\ -0.0234 \end{bmatrix}$$
.

Figure 5 depicts the triggering instants and intervals of ETM (10) while Figures 6-9 show the responses of  $\tilde{x}(t)$  and its estimation.

# IV. CONCLUSION

In this paper, we have considered the problem of estimating state vectors of nonlinear systems with the aid of machine learning. A RNN model which predicts the nonlinear system has been first obtained. Then a discrete-time event-triggered mechanism and a state observer based on this mechanism for the RNN model have been designed. A sufficient condition in terms of a convex optimization problem has been established to ensure that the event-triggered state observer can robustly estimate the state vector of the RNN model. Finally, a numerical example and simulation results are given to illustrate the effectiveness of our proposed design method.



Fig. 5. Triggering instants and intervals of (20)



Fig. 6.  $\tilde{x}_1(t)$  and its estimation

# ACKNOWLEDGMENTS

This paper was completed when the authors were working as researchers at Vietnam Institute for Advance Study in Mathematics (VIASM). The authors would like to thank the VIASM for providing a fruitful research environment and extending support and hospitality during their visit.

#### REFERENCES

- T. Meurer, K. Graichen, E.D. Gilles, *Control and Observer Design for Nonlinear Finite and Infinite Dimensional Systems*. vol. 322 of Lecture Notes in Control and Information Sciences. Springer, 2005.
- [2] T. Fossen, H. Nijmeijer, New Directions in Nonlinear Observer Design. Springer, 1999.
- [3] G. Besançon, Nonlinear Observers and Applications. vol. 363 of Lecture Notes in Control and Information Sciences. Springer, 2007.
- [4] Y. Bar-Shalom, X. R. Li, and T. Kirubarajan, *Estimation with applications to tracking and navigation: theory algorithms and software*. John Wiley & Sons, 2004.
- [5] H. Li, P. Shi, D. Yao and L. Wu, "Observer-based adaptive sliding mode control for nonlinear markovian jump systems," Automatica vol. 64, pp. 133–142, 2016.
- [6] D.C. Huong, H. Trinh, H.M. Tran and T. Fernando, "Approach to fault detection of time-delay systems using functional observers," Electronics Letters vol. 50, no. 6, pp. 1132–1134, 2014.
- [7] H. Trinh and D. C. Huong, "A new method for designing distributed reduced-order functional observers of interconnected time-delay systems," J. Franklin Inst., vol. 355, no. 3, pp. 1411-1451, 2018.



Fig. 7.  $\tilde{x}_2(t)$  and its estimation



Fig. 8.  $\tilde{x}_3(t)$  and its estimation



Fig. 9.  $\tilde{x}_4(t)$  and its estimation

- [8] H. Trinh, D. C. Huong, and S. Nahavandi, "Observers design for positive fractional-order interconnected time-delay systems," *Transactions of the Institute of Measurement and Control*, vol. 41, no. 2, pp. 378-391, 2019.
- [9] D.C. Huong, V.T. Huynh and H. Trinh, "Integral outputs-based robust state observers design for time-delay systems," SIAM J. Control Optim., vol. 57, no. 3, pp. 2214–2239, 2019.
- [10] D. C. Huong, V. T. Huynh, and H. Trinh, "Integral outputs-based robust state observers design for time-delay systems," *SIAM J. Control Optim.*, vol. 57, no. 3, pp. 2214–2239, 2019.
- [11] H. Trinh, D. C. Huong, L. V. Hien, and S. Nahavandi, "Design of reduced-order positive linear functional observers for positive time-delay systems," *IEEE Trans. Circuits Syst. II: Exp. Briefs*, vol. 64, no. 5, pp. 555–559, May. 2017.
- [12] A. Zemouche and M. Boutayeb, "On LMI conditions to design observers for Lipschitz nonlinear systems," Automatica J. IFAC, vol. 49, no. 2, pp. 585–591, 2013.
- [13] L. M. Belmonte, R. Morales, A. F. Caballero, and J. A. Somolinos, "A tandem active disturbance rejection control for a laboratory helicopter with variable-speed rotors," IEEE Trans. Ind. Electron., vol. 63, no. 10,

pp. 6395-6406, Oct. 2016.

- [14] J. Arcos-Legarda, J. Cortes-Romero, and A. Tovar, "Active disturbance rejection control based on generalized proportional integral observer to control a bipedal robot with five degrees of freedom," in Proc. Amer. Control Conf., pp. 3928-3933, Jul. 2016.
- [15] Y. Huang, J. Wang, D. Shi and L. Shi, "Toward event-triggered extended state observer," IEEE Trans. Autom. Control, vol. 63, no. 6, pp. 1842– 1849, Jun. 2018.
- [16] D.C. Huong, V.T. Huynh and H. Trinh, "Dynamic event-triggered state observers for a class of nonlinear systems with time delays and disturbances," IEEE Trans. Circuits Syst. II, Exp. Briefs, vol. 67, no. 12, pp. 3457–3461, 2020.
- [17] D.C. Huong, V.T. Huynh and H. Trinh, "Event-triggered functional observer design with ε-convergence for interconnected systems," IEEE Syst. J., 10.1109/JSYST.2021.3075981.
- [18] J. Sijs and M. Lazar, "Event based state estimation with time synchronous updates," IEEE Trans. Autom. Control, vol. 57, no. 10, pp. 2650–2655, Oct. 2012.
- [19] D.C. Huong, V.T. Huynh and H. Trinh, "Design of event-triggered interval functional observers for systems with input and output disturbances," Mathematical Methods in the Applied Sciences, vol. 44, no. 18, pp. 13968-13978, 2021.
- [20] C. Peng and F. Li, "A survey on recent advances in event-triggered communication and control," Inf. Sci. vol. 457, pp. 113–125, 2018.
- [21] H. Li, X. Liao, T. Huang and W. Zhu, "Event-triggering sampling based leader-following consensus in second-order multi-agent systems," IEEE Transactions on Automatic Control vol. 60, no. 7, pp. 1998–2003, Jul. 2015.
- [22] A. Girard, "Dynamic triggering mechanisms for event-triggered control," IEEE Transactions on Automatic Control vol. 60, no. 7, pp. 1992–1997, Jul. 2015.
- [23] P. Tabuada, "Event-triggered real-time scheduling of stabilizing control tasks," IEEE Transactions on Automatic Control vol. 52, no. 9, pp. 1680– 1685, Sept. 2007.
- [24] L. Xing, C. Wen, Z. Liu, H. Su and J. Cai, "Event-triggered adaptive control for a class of uncertain nonlinear systems," IEEE Transactions on Automatic Control vol. 62, no. 4, pp. 2071–2076, Apr. 2017.
- [25] J. Qiu, K. Sun, T. Wang and H. Gao, "Observer-based fuzzy adaptive event-triggered control for pure-feedback nonlinear systems with prescribed performance," IEEE Transactions on Fuzzy Systems vol. 27, no. 11, pp. 2152–2162, Nov. 2019.
- [26] W. Liu and J. Huang, "Event-triggered global robust output regulation for a class of nonlinear systems," IEEE Transactions on Automatic Control vol. 62, no. 11, pp. 5923–5930, Nov. 2017.
- [27] S. Arik, "Global asymptotic stability of a class of dynamical neural networks," IEEE Transactions on Circuits and Systems-I: Fundamental Theory and Applications, vol. 47, no. 4, pp. 568–571, 2000.
- [28] S. Haykin, Neural Networks: A Comphensive Foundation. Prentice Hall Englewood Cliffs, NJ, 1999.
- [29] B. Zhang, S. Xu, G. Zong, Y. Zou, "Delay-dependent exponential stability for uncertain stochastic Hopfield neural networks with timevarying delays," IEEE Transactions on Circuits and Systems-I: Regular Papers, vol. 56, no. 6, pp. 1241–1247, 2000.
- [30] E. B. Kosmatopoulos, M. M. Polycarpou, M. A. Christodoulou, P. A. Ioannou, "High-order neural network structures for identification of dynamical systems," IEEE Transactions on Neural Networks, vol. 6, no. 2, pp.422-431, 1995.
- [31] Z. Wu, A. Tran, D. Rincon, P.D. Christofides, "Machine learningbased predictive control of nonlinear processes. Part I: Theory," Process Systems Engineering, vol. 65, no. 11, e16734, 2019.
- [32] A. Seuret, F. Gouaisbaut, "Wirtinger-based integral inequality: application to time-delay systems," Automatica, vol. 49, no. 9, pp. 2860–2866, 2013.
- [33] S. Boyd, L.E. Ghaoui, E. Feron, V. Balakrishnan, *Linear Matrix Inequalities in Systems and Control Theory*. SIAM Studies in Applied Mathematics, vol. 15. SIAM, Philadelphia, 1994.
- [34] P. Park, J.M. Ko, C. Jeong, "Reciprocally convex approach to stability of systems with time-varying delays," Automatica, vol. 47, no. 1, pp. 235–238, 2011.
- [35] Y. He, Q. Wang, L. Xie, C. Lin, "Further improvement of free-weighting matrices technique for systems with time-varying delay," IEEE Trans. Autom. Control, vol. 52, no. 2, pp.293–299, 2007.
- [36] Z. Zhang, Z. Wu, D. Rincon, P.D. Christofides, "Real-time optimization and control of nonlinear processes using machine learning," Mathematics, 7, 890, 2019.